





Moeller NK1210+2100+2300-1153GB-INT

Zaštitni motorni prekidači	PKZM01	PKZM0	PKZM4	PKZ2				
								
Strana	→ 4/ 6	→ 4/ 8	→ 4/ 8	→ Main catalogue for industrial switchgear				
Opseg podešavanja sklopke preopterećenja I_r	0.1 – 16 A	0.1 – 32 A	10 – 65 A	0.4 – 40 A				
Podaci za motor pri 400 V	Nazivna snaga motora P kW	Nazivna radna struja I_e A	Nazivna snaga motora P kW	Nazivna radna struja I_e A	Nazivna snaga motora P kW	Nazivna radna struja I_e A	Nazivna snaga motora P kW	Nazivna radna struja I_e A
	0.06	0.21	0.06	0.21				
	0.09	0.31	0.09	0.31				
	0.12	0.41	0.12	0.41			0.12	0.41
	0.18	0.6	0.18	0.6			0.18	0.6
	0.25	0.8	0.25	0.8			0.25	0.8
	0.37	1.1	0.37	1.1			0.37	1.1
	0.55	1.5	0.55	1.5			0.55	1.5
	0.75	1.9	0.75	1.9			0.75	1.9
	1.1	2.6	1.1	2.6			1.1	2.6
	1.5	3.6	1.5	3.6			1.5	3.6
	2.2	5	2.2	5			2.2	5
	3	6.6	3	6.6			3	6.6
	4	8.5	4	8.5			4	8.5
	5.5	11.3	5.5	11.3	5.5	11.3	5.5	11.3
	7.5	15.2	7.5	15.2	7.5	15.2	7.5	15.2
			9	18.2	9	18.2	9	18.2
			11	21.7	11	21.7	11	21.7
			12.5	25	12.5	25	12.5	25
			15	29.3	15	29.3	15	29.3
					18.5	36	18.5	36
					20	40	20	40
					22	41		
					30	55		
					34	63		

Zaštitni motorni prekidači
PKZM01, PKZM0, PKZM4

